Delock Converter USB 3.0 to SATA 6 Gb/s / IDE 40 pin / IDE 44 pin with backup function

Description

This Delock converter enables the connection of 2.5″ or 3.5″ IDE and SATA drives to a USB port of your PC. Thus you can connect your drive, without an external enclosure, directly to your USB port. The included power supply provides power for the converter and the connected drives. The backup function allows backups from your PC to a connected hard drive or SSD.



© 2015 by Delock. All names and symbols mentioned here are property of the respective producer. Printing errors, changes and errors excepted.

Specification

- Connector:
  1 x Micro USB type B female
  1 x DC jack
  1 x 4 pin power connector
  1 x SATA 6 Gb/s 22 pin female
  1 x IDE 40 pin female
  1 x IDE 44 pin female
- Function key:
  1 x On-/ Off switch
  1 x backup button
- For hard drives, SSD, optical drive
- Data transfer rate:
  USB 3.0 up to 5 Gb/s
  SATA up to 6 Gb/s
  IDE up to 133 Mb/s
- With backup function
- Allows simultaneous usage with two IDE drives and a SATA drive
- LED indicator
- Plug & Play

Power supply specification

- Wall power supply
- Input: AC 100 ~ 240 V / 50 ~ 60 Hz / 0.8 A
- Output: 12 V / 2 A
- Ground outside, plus inside
- Dimensions:
  inside: ø ca. 2.5 mm
  outside: ø ca. 5.5 mm
  length: ca. 9.5 mm

System requirements

- Windows Vista/Vista-64/7/7-64/8/8-64/8.1/8.1-64
- PC or notebook with a free USB port

Item No. 61486



EAN	4043619614868
Country of origin	China

Package content

- Converter USB 3.0 > SATA / IDE
- USB 3.0 cable
- Power cable
- External power supply
- CD ROM with software
- User manual

Package

- Retail Box

© 2015 by Delock. All names and symbols mentioned here are property of the respective producer. Printing errors, changes and errors excepted.

Images









© 2015 by Delock. All names and symbols mentioned here are property of the respective producer. Printing errors, changes and errors excepted.